4. Electrical Parts List

Loc.No	Part No	Description ; Specification	Remark
601		**ASSY PCB-MAIN;**	
POWER DRIVE PARTS			
C1P102	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P103	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P104	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P105	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P106	2401-000463	C-AL;10UF,20%,35V,GP,-,5X5,5	
C1P107	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P109	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P110	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P111	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5	
C1P112	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P113	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P114	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P115	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C1P116	2401-003122	C-AL;4.7uF,20%,50V,LL,TP,4X7,1.5	
C1P117	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C1P118	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C1P119	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5	
CN01	3711-000683	CONNECTOR-HEADER;BOX,13P,1R,2mm,STRAIGHT	
CN02	3708-001085	CONNECTOR-FPC/FFC/PIC;40P,1.25MM,STRAIGH	
CN02A	3809-001181	CABLE-FLAT;30V,-30to+80C,80mm,40P,1.25mm	
D1P101	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D1P102	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D1P103	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P104	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P105	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P107	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P108	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P109	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D1P110	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
L1P101	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
Q1P101	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P102	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P103	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P104	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P105	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P106	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P107	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P108	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P109	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P110	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P111	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P112	0501-000616	TR-SMALL SIGNAL;KSC2328A-Y,NPN,1W,TO-92L	
Q1P113	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q1P114	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q1P115	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
R1P101	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P103	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P104	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P105	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P109	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P110	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P111	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R1P112	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P115	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1P116	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1P120	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
ZD1P02	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD1P03	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
ZD1P04	0403-000717	DIODE-ZENER;MTZJ5.1B,5.1V,4.94-5.2V,500m	
ZD1P05	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
ZD1P06	0403-000717	DIODE-ZENER;MTZJ5.1B,5.1V,4.94-5.2V,500m	
ZDP107	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
SYSTEM CONTROL/SERVO PARTS			
C601	2203-000609	C-CER,CHIP;22nF,10%,50V,X7R,TP,2012	
C602	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C605	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C606	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C607	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C608	2401-002259	C-AL;0.1F,+80-20%,5.5V,-,TP,12.	BACK-UP 1Hour Only
C610	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C618	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
C619	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C623	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C624	2203-000634	C-CER,CHIP;0.022NF,5%,50V,C0G,T	BACK-UP 1Hour Only
C625	2203-000634	C-CER,CHIP;0.022NF,5%,50V,C0G,T	BACK-UP 1Hour Only
C626	2203-000634	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,2012	
C627	2203-000634	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,2012	
C632	2203-000802	C-CER,CHIP;33nF,10%,50V,X7R,TP,2012	
C633	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C634	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C635	2202-000183	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R,TP	
C636	2202-000183	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R,TP	
C637	2203-000938	C-CER,CHIP;0.47NF,5%,50V,C0G,TP,2012	
C638	2401-002196	C-AL;4.7UF,20,25V,GP,TP,4X5,5MM,-	
C639	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C640	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C641	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C642	2401-001507	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
C645	2203-000361	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,2012	
C646	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C659	2203-001137	C-CER,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,	
C661	2203-000989	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
C688	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C691	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C695	2203-000361	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,2012	
C696	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP	
C697	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C698	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
CN603	3710-001146	CONNECTOR-SOCKET;20P,1R,1.5mm,ANGLE,SN	
CN604	3711-004833	CONNECTOR-HEADER;BOX,12P,2R,2MM,STRAIGHT	
D603	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D620	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D688	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D692	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
IC601	AC09-00274A	IC MICOM;UPD78F4928GF-3BA,FRESH ROM,100	
IC604	AC14-12009W	IC-RESET;PST572K,TO-92,R59-1766 2.5V	
IC605	1103-001171	IC-EEPROM;L51DC,16KBit,DIP,8P,300MIL,10m	
IC608	1203-000515	IC-VOL. DETECTOR;7042,TO-92,3P,	BACK-UP 1Hour Only
J602	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J603	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J604	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J605	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J606	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
J607	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
L603	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
L605	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
LD601	0601-000517	LED-IR;RECTANGULA,4x6.0mm,75mW,6V,950	
PT601	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	

Loc.No	Part No	Description ; Specification	Remark
PT602	0604-001206	PHOTO-INTERRUPTER;TR,-,150mW,CY5894102,B	
Q601	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q602	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R605A	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R608	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R609	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R613	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	BACK-UP 1Hour Only
R614	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R615	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R617	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R620	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R621	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R630	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R631	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R640	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R641	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R642	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R644	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R647	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R651	2007-000001	R-CHIP;68Kohm,5%,1/8W,TP,2012	
R652	2007-000658	R-CHIP;27ohm,5%,1/8W,TP,2012	BACK-UP 1Hour Only
R657	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	Other Only
	2007-000001	R-CHIP;68Kohm,5%,1/8W,TP,2012	BACK-UP 1Hour Only
R660	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R661	2007-000774	R-CHIP;33Kohm,5%,1/8W,TP,2012	
R666	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R667	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R668	2007-000931	R-CHIP;470ohm,5%,1/8W,TP,2012	
R669	2007-000931	R-CHIP;470ohm,5%,1/8W,TP,2012	
R670	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R671	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R672	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R673	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R674	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R675	2001-000032	R-CARBON;180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R676	2007-000738	R-CHIP;30Kohm,5%,1/8W,TP,2012	
R677	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2007-000586	R-CHIP;22Kohm,5%,1/8W,TP,2012	
R679	2007-000572	R-CHIP;220ohm,5%,1/8W,TP,2012	
R682	2007-000586	R-CHIP;22Kohm,5%,1/8W,TP,2012	
R685	2007-000981	R-CHIP;5.6Kohm,5%,1/8W,TP,2012	
R688	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R691	2007-000572	R-CHIP;220ohm,5%,1/8W,TP,2012	
R693	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R694	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R698	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
S601	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
S602	0603-001011	PHOTO TR;NPN,35V,6V,50mA,75mW,BK	
SW601	AC34-20100A	SWITCH-MODE;-,-,X-9,-	
SW602	AC34-20100B	SWITCH-REC;-,-,X-9,-	
XT601	2801-003318	CRYSTAL-UNIT;32.768KHz,20ppm,28	BACK-UP 1Hour Only
XT602	2801-003139	CRYSTAL-UNIT;8MHz,50ppm,28-AAA,22pF,80oh	
A/V PARTS			
C315	2203-000989	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
C317	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C318	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C319	2203-000844	C-CER,CHIP;39nF,10%,50V,X7R,TP,2012,-	
C320	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C321	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C322	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C324	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C325	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C326	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	

Loc.No	Part No	Description ; Specification	Remark
C327	2202-000720	C-CERAMIC,MLC-AXIAL;8.2nF,20%,16V,Y5R,TP	
C328	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C329	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C330	2203-000989	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
C331	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	SECAM Only
	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	Other Only
C332	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C333	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C334	2203-000989	C-CER,CHIP;47nF,10%,50V,X7R,TP,2012	
C335	2203-000925	C-CER,CHIP;470NF,+80-20%,50V,Y5V,TP,2012	
C336	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C337	2203-000925	C-CER,CHIP;470NF,+80-20%,50V,Y5V,TP,2012	
C338	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C339	2401-000426	C-AL;10uF,20%,16V,GP,TP,3.5x5,5	
C340	2401-001226	C-AL;4.7uF,20%,16V,BP,TP,4x7,5mm	
C341	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C342	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C343	2203-000476	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,TP,201	
C344	2203-000321	C-CER,CHIP;0.12nF,5%,50V,SL,TP,2012	
C345	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
C347	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C348	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C349	2203-000476	C-CER,CHIP;1000nF,+80-20%,16V,Y5V,TP,201	
C350	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C351	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C352	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C353	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C354	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C355	2202-002055	C-CERAMIC,MLC-AXIAL;47nF,+80-20%,50V,Y5V	
C372	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C380	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C384	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C385	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C393	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C395	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C396B	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
C3A01	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C3A02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3A08	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A09	2203-001105	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,2012	
C3A10	2203-001214	C-CER,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
C3A11	2301-000180	C-FILM,LEAD-PEF;18nF,0.05,100V,TP,7.2x4.	
C3A12	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3A14	2203-000938	C-CER,CHIP;0.47NF,5%,50V,C0G,TP,2012	
C3A15	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3A16	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C3A17	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A18	2203-001128	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,2012	
C3A21	2203-000170	C-CER,CHIP;1.8nF,10%,50V,X7R,TP,2012	
C3A23	2401-002069	C-AL;33uF,20%,16V,GP,TP,6.3x5,5	
C3A24	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A29	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C3A30	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3A40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C3A41	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3D01	2301-000224	C-FILM,LEAD-PEF;22nF,5%,50V,TP,7.4x3.9x1	
C3D02	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3D03	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C3D04	2203-000938	C-CER,CHIP;0.47NF,5%,50V,C0G,TP,2012	
C3Q1	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3Q2	2203-000818	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,2012	
C3Q3	2203-001088	C-CER,CHIP;0.005nF,0.25pF,50V,NP0,TP,201	
C3Q4	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
CN301	3708-000391	CONNECTOR-FPC/FFC/PIC;10P,1.25MM,STRAIGH	
CN3A01	3708-001165	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT	
CN3A02	3710-001648	CONNECTOR-SOCKET;2P,1R,2.5mm,STRAIGHT,SN	

Loc.No	Part No	Description ; Specification	Remark
CN3A1S	3809-001206	CABLE-FLAT;30V,-20to+80C,140mm,6P,1.25mm	
D301	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D302	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
FL3A01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
FL3D01	2702-000166	INDUCTOR-RADIAL;47uH,5%,6.0x6.4mm	
IC301	1204-002140	IC-VIDEO PROCESS;LA71750EM-MPB-E,QFP,100	
L302	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L303	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
L370	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A01	2702-000120	INDUCTOR-RADIAL;15000uH,5%,6.2x7.4mm	
L3A02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L3A03	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
L3A50	2702-000119	INDUCTOR-RADIAL;150uH,5%,6.0x6.4mm	
L3D01	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
L3Q1	2701-000206	INDUCTOR-AXIAL;56uH,5%,2434	
L3Q2	2701-000131	INDUCTOR-AXIAL;15uH,5%,2534	
Q302	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q350	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q351	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A01	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3A02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3A03	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A04	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A05	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3A06	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3D01	0501-000442	TR-SMALL SIGNAL;KTC3203-Y,NPN,400mW,T0-9	
Q3D02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q3D07	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q3Q1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q4	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q3Q5	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q3Q6	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q3Q7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R315	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R316	2007-001177	R-CHIP;8.2Kohm,5%,1/8W,TP,2012	
R320	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R321	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R322	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R323	2007-000710	R-CHIP;3.9Kohm,5%,1/8W,TP,2012	
R324	2007-000267	R-CHIP;1.8Kohm,5%,1/8W,TP,2012	
R325	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R326	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R327	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R328	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R329	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	
R330	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R331	2007-000267	R-CHIP;1.8Kohm,5%,1/8W,TP,2012	
R333	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
R334	2007-000241	R-CHIP;1.5Kohm,5%,1/8W,TP,2012	
R335	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R350	2007-000241	R-CHIP;1.5Kohm,5%,1/8W,TP,2012	
R360	2007-001195	R-CHIP;820Kohm,5%,1/8W,TP,2012	
R370	2007-000030	R-CHIP;560ohm,5%,1/8W,TP,2012	
R371	2001-000855	R-CARBON;560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R372	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R373	2007-000546	R-CHIP;20Kohm,5%,1/8W,TP,2012	
R374	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R380	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	
R3A01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A04	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R3A05	2007-000615	R-CHIP;24Kohm,5%,1/8W,TP,2012	
R3A06	2007-000401	R-CHIP;150ohm,5%,1/8W,TP,2012	
R3A07	2007-000757	R-CHIP;330Kohm,5%,1/8W,TP,2012	
R3A08	2007-000355	R-CHIP;12Kohm,5%,1/8W,TP,2012	
R3A09	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
R3A11	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	
R3A12	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R3A13	2007-000586	R-CHIP;22Kohm,5%,1/8W,TP,2012	
R3A14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A16	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R3A17	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	
R3A18	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	
R3A23	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A24	2007-000586	R-CHIP;22Kohm,5%,1/8W,TP,2012	
R3A25	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R3A26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A28	2007-000267	R-CHIP;1.8Kohm,5%,1/8W,TP,2012	
R3A50	2007-000710	R-CHIP;3.9Kohm,5%,1/8W,TP,2012	
R3A51	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R3A60	2001-000605	R-CARBON;3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R3D01	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R3D02	2007-000872	R-CHIP;4.7Kohm,5%,1/8W,TP,2012	
R3D03	2007-000586	R-CHIP;22Kohm,5%,1/8W,TP,2012	
R3D04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q1	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R3Q12	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3Q2	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R3Q3	2007-000766	R-CHIP;330ohm,5%,1/8W,TP,2012	
R3Q4	2007-001055	R-CHIP;6.2Kohm,5%,1/8W,TP,2012	
R3Q5	2007-000766	R-CHIP;330ohm,5%,1/8W,TP,2012	
R3Q6	2007-000258	R-CHIP;1.6Kohm,5%,1/8W,TP,2012	
R3Q7	2007-000844	R-CHIP;3Kohm,5%,1/8W,TP,2012	
R3Q8	2007-000766	R-CHIP;330ohm,5%,1/8W,TP,2012	
R3Q9	2007-001155	R-CHIP;750ohm,5%,1/8W,TP,2012	
XT301	2801-001397	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAA,S,	
TM-BLOCK PARTS			
C401	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C402	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
C403	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C404	2401-001085	C-AL;330nF,20%,50V,GP,-.5x9,2mm	
C405	2401-003046	C-AL;47uF,20%,50V,WT,TP,6.3x11,2.5	
C406	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C407	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C408	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C409	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	
C410	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
CE401	2401-001353	C-AL;470uF,20%,10V,GP,TP,8x11.5,5	
R401	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R402	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R403	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R404	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R406	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R408	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
TM401	AC40-00001T	TM BLOCK;TCPL0601PD23A,G/L-SPLITTER,-,-	SECAM Only
	AC40-00016A	TM BLOCK;TMDG2-831A,PAL-G//K	MESECAM Only
ZD401	0403-000390	DIODE-ZENER;UZP33B,33V,31.4-34.6V,1W,DO-	
HI-FI PARTS			
C501	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C502	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C503	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C504	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C505	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C506	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C507	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C508	2203-000891	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C510	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C511	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C513	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
C517	2203-000891	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,2012	
C518	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C519	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C520	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C521	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C522	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C523	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C524	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C525	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C526	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C527	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C529	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C530	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C535	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C536	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C537	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C538	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C539	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C540	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C541	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C542	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
D501	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
IC501	1204-001920	IC-AUDIO PROCESSOR;LA72646M,QFP,80P,14X1	
R501	2007-000653	R-CHIP;27Kohm,5%,1/8W,TP,2012	
R502	2007-001055	R-CHIP;6.2Kohm,5%,1/8W,TP,2012	
R503	2007-000931	R-CHIP;470ohm,5%,1/8W,TP,2012	
R505	2007-000653	R-CHIP;27Kohm,5%,1/8W,TP,2012	
R506	2007-001055	R-CHIP;6.2Kohm,5%,1/8W,TP,2012	
R507	2001-000679	R-CARBON;36KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R508	2007-001055	R-CHIP;6.2Kohm,5%,1/8W,TP,2012	
R509	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R510	2007-000738	R-CHIP;30Kohm,5%,1/8W,TP,2012	
R511	2007-000409	R-CHIP;15Kohm,5%,1/8W,TP,2012	
R512	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R517	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R518	2007-000738	R-CHIP;30Kohm,5%,1/8W,TP,2012	
R519	2007-001055	R-CHIP;6.2Kohm,5%,1/8W,TP,2012	
R520	2001-000679	R-CARBON;36KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R521	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R522	2007-001071	R-CHIP;6.8Kohm,5%,1/8W,TP,2012	
R533	2007-000738	R-CHIP;30Kohm,5%,1/8W,TP,2012	
R540	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R545	2007-000511	R-CHIP;2.4Kohm,5%,1/8W,TP,2012	
R546	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
R547	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
R550	2001-000766	R-CARBON;43KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R551	2007-000546	R-CHIP;20Kohm,5%,1/8W,TP,2012	
R552	2007-000003	R-CHIP;43Kohm,5%,1/8W,TP,2012	
R553	2007-000546	R-CHIP;20Kohm,5%,1/8W,TP,2012	
R570	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R571	2007-001039	R-CHIP;56Kohm,5%,1/8W,TP,2012	
SECAM PARTS		**SECAM Only**	
C3S01	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3S02	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S03	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C3S04	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C3S05	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C3S06	2401-001775	C-AL;470nF,20%,50V,GP,TP,4x7,5	
C3S07	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C3S08	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C3S09	2401-001775	C-AL;470nF,20%,50V,GP,TP,4x7,5	
C3S10	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C3S11	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C3S12	2301-000008	C-FILM,LEAD-PEF;2.2nF,5%,50V,TP,5.5X7X3,	
C3S13	2301-000008	C-FILM,LEAD-PEF;2.2nF,5%,50V,TP,5.5X7X3,	
C3S14	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C3S15	2203-000444	C-CER,CHIP;1nF,10%,50V,X7R,TP,2012,-	
IC3S01	1204-001921	IC-CHROMA;LA70100M,SOP,30P,375MIL,PLASTI	
R3S01	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R3S02	2007-000477	R-CHIP;1Mohm,5%,1/8W,TP,2012	
A2/NICAM PARTS			
C4N01	2203-000142	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,2012	
C4N02	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N03	2203-000595	C-CER,CHIP;0.22NF,5%,50V,C0G,TP,2012	
C4N04	2401-000665	C-AL;2.2uF,20%,50V,GP,TP,3.5x5,5	
C4N05	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C4N06	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C4N07	2203-000938	C-CER,CHIP;0.47NF,5%,50V,C0G,TP,2012	
C4N08	2203-000142	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,2012	
C4N09	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N10	2401-000426	C-AL;10uF,20%,16V,GP,TP,3.5x5,5	
C4N11	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5	
C4N12	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C4N13	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C4N14	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
C4N15	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C4N16	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C4N17	2203-000938	C-CER,CHIP;0.47NF,5%,50V,C0G,TP,2012	
C4N18	2203-000938	C-CER,CHIP;0.47NF,5%,50V,C0G,TP,2012	
C4N19	2202-000279	C-CERAMIC,MLC-AXIAL;47pF,5%,50V,SL,TP,3.	
C4N21	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N22	2201-002069	C-CERAMIC,DISC;0.0015NF,0.25PF,50V,C0G,T	
C4N25	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V	
C4N30	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
D4N01	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D4N02	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
IC4N01	1204-001765	IC-AUDIO PROCESSOR;MSP3417D(PQFP),PQFP,4	
L4N01	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N02	2702-000106	INDUCTOR-RADIAL;100uH,10%,6.2x7.4mm	
L4N03	2702-000160	INDUCTOR-RADIAL;4.7uH,10%,6.0x6.4mm	
L4N04	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
R4N01	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R4N02	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R4N03	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R4N04	2007-000653	R-CHIP;27Kohm,5%,1/8W,TP,2012	
R4N05	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R4N06	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
XT4N01	2801-004096	CRYSTAL-UNIT;18.432MHZ,20PPM,28-AAA,16PF	
OSD/VPS/PDC PARTS			
C6P01	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C6P02	2203-000321	C-CER,CHIP;0.12nF,5%,50V,SL,TP,	NTSC 4.44 Only
C6P04	2203-000683	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,2012	
C6P05	2203-000683	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,2012	
C6P07	2401-002299	C-AL;4.7uF,20%,50V,GP,TP,5x7,5	NTSC 4.43 Only
C6P08	2203-001077	C-CER,CHIP;0.056nF,5%,50V,NP0,TP,2012	
C6P10	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P11	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C6P12	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C6P13	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
C6P15	2203-001137	C-CER,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,	
D6P01	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
IC6P01	1204-001797	IC-OSD PROCESSOR;LC74776NM-9821,MPF,30P,	
	1204-001796	IC-OSD PROCESSOR;LC74759JM-9820	NTSC 4.44 Only
L6P03	2702-000142	INDUCTOR-RADIAL;22uH,5%,6.0x6.4mm	
L6P05	2702-000144	INDUCTOR-RADIAL;27uH,5%,6.0x6.4mm	
Q6P01	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q6P02	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
Q6P04	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R6P01	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	NTSC 4.43 Only

Loc.No	Part No	Description ; Specification	Remark
R6P02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	NTSC 4.43 Only
R6P03	2007-000518	R-CHIP;2.7Kohm,5%,1/8W,TP,2012	NTSC 4.43 Only
R6P04	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	NTSC 4.43 Only
R6P04	2203-000444	C-CER,CHIP;1nF,10%,50V,X7R,TP,2012,-	NTSC 4.43 Only
R6P05	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R6P06	2007-000981	R-CHIP;5.6Kohm,5%,1/8W,TP,2012	NTSC 4.43 Only
R6P07	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P08	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R6P09	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
	2007-000493	R-CHIP;2.2Kohm,5%,1/8W,TP,2012	NTSC 4.44 Only
R6P10	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R6P12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R6P13	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R6P14	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
INPUT-OUTPUT PARTS			
J751	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
ZD701	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
C801	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C802	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C804	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C805	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C806	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C807	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C808	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C809	2401-001250	C-AL;4.7uF,20%,35V,GP,TP,4x5,5	
C810	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C811	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C812	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C813	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C814	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C815	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C816	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C817	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C818	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C819	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C820	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C821	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C822	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C823	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C824	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C824A	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C825	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C826	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C827	2203-000533	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
C828	2203-000533	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
C829	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C830	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C833	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C835	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C836	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C851	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C852	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C853	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C854	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C855	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C856	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C857	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C858	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C859	2203-000260	C-CER,CHIP;10nF,10%,50V,X7R,TP,2012	
C860	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C861	2203-000239	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,2012	
C862	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C863	2203-000784	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,2012	
C890	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C890B	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	

Loc.No	Part No	Description ; Specification	Remark
C891	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C891B	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
C899	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
C904A	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
D805	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
IC801	0801-002741	IC-CMOS LOGIC;BU4053BCFV,MUX,SSOP,16P,17	
IC802	0801-002741	IC-CMOS LOGIC;BU4053BCFV,MUX,SSOP,16P,17	
IC803	0801-002741	IC-CMOS LOGIC;BU4053BCFV,MUX,SSOP,16P,17	
J999	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
JC801	3722-001345	JACK-SCART;42P/2R,-,SN,BLK,-	
JC802	AC37-20001G	JACK-RCA;DPAE-,6P,HIFI,PI3.3	
L802	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
L803	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L804	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L805	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L806	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L807	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L808	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L809	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L810	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L811	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L812	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L814	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
L815	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
L816	2701-000181	INDUCTOR-AXIAL;33uH,5%,2434	
Q802	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q803	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q804	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q806	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q807	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q808	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q809	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q810	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q811	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q812	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q820	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
Q821	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q890	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q890A	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q890B	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
Q891	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q891A	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
Q891B	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
R801	2007-000653	R-CHIP;27Kohm,5%,1/8W,TP,2012	
R802	2007-000267	R-CHIP;1.8Kohm,5%,1/8W,TP,2012	
R803	2007-000267	R-CHIP;1.8Kohm,5%,1/8W,TP,2012	
R804	2007-000653	R-CHIP;27Kohm,5%,1/8W,TP,2012	
R805	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R806	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R807	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
R808	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
R809	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
R810	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R811	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R812	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
R813	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R814	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R815	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R816	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R819	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R820	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R821	2007-000774	R-CHIP;33Kohm,5%,1/8W,TP,2012	
R822	2007-000586	R-CHIP;22Kohm,5%,1/8W,TP,2012	
R823	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R825	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R827	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
R828	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R829	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R830	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R831	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R832	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R833	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R834	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R835	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R836	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R839	2007-000290	R-CHIP;100ohm,5%,1/8W,TP,2012	
R841	2007-000030	R-CHIP;560ohm,5%,1/8W,TP,2012	
R842	2007-000030	R-CHIP;560ohm,5%,1/8W,TP,2012	
R843	2007-000030	R-CHIP;560ohm,5%,1/8W,TP,2012	
R844	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
R851	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R852	2007-000941	R-CHIP;47Kohm,5%,1/8W,TP,2012	
R853	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R854	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R855	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R856	2007-001208	R-CHIP;82Kohm,5%,1/8W,TP,2012	
R858	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R859	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
R860	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R861	2007-000468	R-CHIP;1Kohm,5%,1/8W,TP,2012	
R891	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R891B	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R892	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R892B	2007-001177	R-CHIP;8.2Kohm,5%,1/8W,TP,2012	
R893	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R893B	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R894	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R894B	2007-000300	R-CHIP;10Kohm,5%,1/8W,TP,2012	
R895	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R895B	2007-001177	R-CHIP;8.2Kohm,5%,1/8W,TP,2012	
R896	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R896B	2007-000221	R-CHIP;1.2Kohm,5%,1/8W,TP,2012	
R899	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W238	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W239	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W401	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W442	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W444	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W450	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W454	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W455	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W467	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W680	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
W701	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W705	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W737	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W888	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
W896	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
W897	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
ZD801	0403-000297	DIODE-ZENER;MTZ6.2B,6.2V,5.96-6.27V,500m	
ZD802	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD803	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD804	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD805	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD806	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD807	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD808	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD809	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD810	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD811	2007-001166	R-CHIP;75ohm,5%,1/8W,TP,2012	
ZD812	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD813	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD814	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZD817	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
602	**AK92-00360A**	**ASSY PCB-MAIN AMP;CHT-200/XEL,DVD MAIN A**	**Other Only**
	AK92-00381A	**ASSY PCB-MAIN AMP;DVD-CM200/XEV,DVD MAIN**	**CIS Only**
AC14	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,TP,1608	
AC21	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
AC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
AC23	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	
AC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
AC25	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608	
AC26	2203-000125	C-CER,CHIP;1.2nF,10%,50V,X7R,TP,1608,-	
AC27	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
AC9	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,TP,1608	
AD1	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD2	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AD4	0401-000008	DIODE-SWITCHING;DAN217,80V,100mA,SOT-23,	
AD5	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
AE11	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
AE12	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
AE13	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
AE14	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
AE15	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5	
AE16	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AE21	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
AE3	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
AE5	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
AIC101	1201-001909	IC-AUDIO AMP;TAS5110,TSSOP,32P,11X6.2MM,	
AIC151	1201-001909	IC-AUDIO AMP;TAS5110,TSSOP,32P,11X6.2MM,	
AIC201	1201-001909	IC-AUDIO AMP;TAS5110,TSSOP,32P,11X6.2MM,	
AIC251	1201-001909	IC-AUDIO AMP;TAS5110,TSSOP,32P,11X6.2MM,	
AIC300	1201-001909	IC-AUDIO AMP;TAS5110,TSSOP,32P,11X6.2MM,	
AIC4	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
AIC401	1201-001909	IC-AUDIO AMP;TAS5110,TSSOP,32P,11X6.2MM,	
AQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ6	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
AQ7	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
AQ8	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
AQ9	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
AR101	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
AR14	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
AR15	2007-001044	R-CHIP;56ohm,5%,1/10W,TP,1608	
AR151	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
AR16	2007-001044	R-CHIP;56ohm,5%,1/10W,TP,1608	
AR17	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR28	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
AR29	2007-001044	R-CHIP;56ohm,5%,1/10W,TP,1608	
AR30	2007-001044	R-CHIP;56ohm,5%,1/10W,TP,1608	
AR31	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR41	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
AR42	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR43	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
AR44	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
AR45	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
AR46	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
AR47	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR48	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
AR49	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
AR50	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
AR51	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
AR53	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
AR54	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
AR55	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
AR60	2007-001135	R-CHIP;68ohm,5%,1/4W,TP,3216	
CN101	3708-001085	CONNECTOR-FPC/FFC/PIC;40P,1.25MM,STRAIGH	
CON102	AC39-00081A	CBF HARNESS;-,24AWG,-,10P,80,-,-,-,MOLEX	

Loc.No	Part No	Description ; Specification	Remark
DAC10	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC101	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
DAC102	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
DAC103	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC104	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608	
DAC105	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC107	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC109	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC11	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC111	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC112	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC113	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC114	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC115	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
DAC116	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC117	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC14	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC15	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC16	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC17	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC18	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC2	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC6	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DAC9	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
DAD1	0407-000114	DIODE-ARRAY;DAN202K,80V,100mA,CA2-3,SOT-	
DAD101	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
DAIC11	1204-002040	IC-MODULATOR;TAS5026CPAG,TQFP,64P,10X10M	
DAIC12	0801-002781	IC-CMOS LOGIC;SN74LV123APWR,MONO - MULTI	
DAIC13	0801-002780	IC-CMOS LOGIC;SN74LVC1G17,SCHMITT-TRIGGE	
DAIC14	1205-002191	IC-CODEC;AK4586VQ,LQFP,44P,10X10MM,PLAS	
DAIC16	0801-002779	IC-CMOS LOGIC;SN74LVC1G125DBVR,BUS BUFFE	
DAIC17	0505-001679	FET-SILICON;FDC6301N,N,25V,0.22A,5OHM,0.	
DAL2	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
DAL3	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
DAR1	2007-000502	R-CHIP;2.2ohm,5%,1/8W,TP,2012	
DAR101	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
DAR102	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR103	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
DAR104	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012	
DAR105	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
DAR107	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DAR108	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DAR11	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR111	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012	
DAR112	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR113	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012	
DAR114	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
DAR12	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR13	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR14	2007-000458	R-CHIP;18Kohm,5%,1/10W,TP,1608	
DAR18	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
DAR19	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608	
DAR2	2007-000881	R-CHIP;4.7ohm,5%,1/8W,TP,2012	
DAR20	2007-000881	R-CHIP;4.7ohm,5%,1/8W,TP,2012	
DAR21	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
DAR27	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DAR28	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DAR3	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR4	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR5	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR6	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
DAR7	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR8	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DAR9	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
DC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
DCN1	3708-001696	CONNECTOR-FPC/FFC/PIC;24P,1MM,STRAIGHT,S	
DCN2	3708-001695	CONNECTOR-FPC/FFC/PIC;13P,1MM,STRAIGHT,S	
DCN3	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
DD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-	
DQ1	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
DQ2	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
DQ3	0501-000341	TR-SMALL SIGNAL;KSC1623-L,NPN,200mW,SOT-	
DR1	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR2	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR3	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
DR4	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR5	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
DR6	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
DR7	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
DR8	2007-000116	R-CHIP;120ohm,5%,1/10W,TP,1608	
FC1	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
FC2	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
FC3	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
FC4	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
FC5	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
FC6	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
FR1	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR10	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR11	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR3	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR4	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR5	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR6	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR7	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR8	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
FR9	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MC1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
MC14	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC15	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
MC16	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
MC17	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
MC18	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
MC2	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC3	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC4	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC5	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
MC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
MC8	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MC9	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
MIC1	0903-001288	IC-MICROCONTROLLER;ZR36705,32BIT,QFP,100	
MIC2	1107-001369	IC-FLASH MEMORY;MBM29LV800BA-90PFTN,512K	
MIC3	0801-001072	IC-CMOS LOGIC;74ACT32,OR GATE,SOP,14,150	
MIC4	1103-001204	IC-EEPROM;24C021,256x8Bit,SOP,8P,150MIL,	
MR1	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR10	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR11	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR12	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR13	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR14	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR16	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR17	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR18	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR19	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
MR2	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR20	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR24	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR25	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
MR26	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
MR27	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR28	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR3	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
MR31	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR32	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR35	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR37	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR38	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR39	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR40	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR41	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR42	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR43	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR44	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR45	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR46	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR47	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR48	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
MR49	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
MR50	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR51	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
MR52	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
MR53	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
MR55	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
MR56	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR57	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR58	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR59	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR6	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
MR60	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR61	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR62	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR63	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR64	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MR7	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608	
MR8	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
MR9	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
MY1	2802-001154	RESONATOR-CERAMIC;12.5MHZ,0.5%,TP,10.0X5	
PAC101	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PAC102	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
PACC1	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
PACC10	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
PACC11	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACC12	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACC13	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACC14	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACC15	2401-003580	C-AL;1000uF,20%,35V,WT,TP,13x20mm,5	
PACC16	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
PACC17	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PACC3	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACC4	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACC5	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACC6	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACC7	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACC8	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACC9	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACF1	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
PACF10	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF11	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF12	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	

Loc.No	Part No	Description ; Specification	Remark
PACF13	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF14	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF15	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACF16	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACF17	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACF18	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACF19	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
PACF2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PACF20	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
PACF21	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACF22	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACF23	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACF24	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACF25	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACF26	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACF27	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACF28	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACF29	2401-003580	C-AL;1000uF,20%,35V,WT,TP,13x20mm,5	
PACF3	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
PACF30	2401-003580	C-AL;1000uF,20%,35V,WT,TP,13x20mm,5	
PACF31	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
PACF32	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACF4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PACF5	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF6	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF7	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF8	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACF9	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR1	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
PACR10	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR11	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR12	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR13	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR14	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR15	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACR16	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACR17	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACR18	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACR19	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
PACR2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PACR20	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP,-,5mm	
PACR21	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACR22	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACR23	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACR24	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACR25	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACR26	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACR27	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACR28	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACR29	2401-003580	C-AL;1000uF,20%,35V,WT,TP,13x20mm,5	
PACR3	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
PACR30	2401-003580	C-AL;1000uF,20%,35V,WT,TP,13x20mm,5	
PACR31	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
PACR32	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACR4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PACR5	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR6	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR7	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR8	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACR9	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACW10	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACW11	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACW13	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACW14	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACW17	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	
PACW18	2203-005757	C-CER,CHIP;33nF,10%,200V,X7R,TP,3216	

Loc.No	Part No	Description ; Specification	Remark
PACW20	2305-000412	C-FILM,LEAD-PEF;470nF,5%,63V,TP;-,5mm	
PACW23	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACW24	2301-001549	C-FILM,LEAD-PEF;390NF,5%,50V,TP,7.3X5.7X	
PACW25	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACW26	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACW28	2401-003580	C-AL;1000uF,20%,35V,WT,TP,13x20mm,5	
PACW29	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
PACW3	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
PACW30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PACW4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PACW6	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PACW9	2203-000206	C-CER,CHIP;100nF,10%,50V,X7R,TP,2012	
PAE101	2401-001130	C-AL;330uF,20%,35V,GP,TP,10x16,5	
PALC3	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALC4	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALF5	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALF6	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALF7	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALF8	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALR5	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALR6	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALR7	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALR8	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALW7	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PALW8	AK27-00001A	COIL CHOKE;SBPSC-11R310-100A,SBPSC COILS	
PAR103	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PAR104	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012	
PARC1	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARC2	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARC3	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARC4	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARC5	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARC6	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARC7	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARC8	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARC9	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARF1	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARF10	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARF11	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARF12	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARF13	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARF14	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARF15	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARF16	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARF17	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARF2	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARF3	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARF4	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARF5	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARF6	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARF7	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARF8	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARF9	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARR10	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARR11	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARR12	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARR13	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARR14	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARR15	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARR16	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARR17	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARR18	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARR19	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARR3	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARR4	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARR5	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARR6	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARR7	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARR8	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARR9	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARW11	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARW12	2007-008541	R-CHIP,MELF;1.5OHM,1%,1/4W,-,TP,1.4X3.6M	
PARW13	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARW14	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARW15	2007-002425	R-CHIP;1ohm,5%,1/10W,TP,1608	
PARW3	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARW4	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608	
PARW6	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PARW8	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
PC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC11	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC14	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC5	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
PC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
PE1	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE10	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE11	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE12	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE2	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
PE3	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE4	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE5	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE6	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
PE7	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
PE8	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
PE9	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5	
PIC1	1203-002178	IC-VOLTAGE REGULATOR;1563,SOP,7P,173MIL,	
PIC2	1203-002577	IC-VOLTAGE REGULATOR;MIM1561J,SOP,7P,173M	
PIC3	1203-002185	IC-VOLTAGE REGULATOR;3RD13,TO-220,4P,402	
PIC5	1203-002185	IC-VOLTAGE REGULATOR;3RD13,TO-220,4P,402	
PL1	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
PL2	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
PL3	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
PL7	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
PR1	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
PR4	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
PR5	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
RC1	2203-000560	C-CER,CHIP;220nF,+80-20%,25V,Y5V,TP,1608	
RC14	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC16	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC17	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
RC18	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
RC19	2203-000560	C-CER,CHIP;220nF,+80-20%,25V,Y5V,TP,1608	
RC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC20	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
RC21	2203-000560	C-CER,CHIP;220nF,+80-20%,25V,Y5V,TP,1608	
RC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC23	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC25	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RC26	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	

Loc.No	Part No	Description ; Specification	Remark
RC27	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
RC31	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
RC32	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC33	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,TP,160	
RC34	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-	
RC35	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC37	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608	
RC38	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
RC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC41	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC50	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,TP,1608	
RC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
RC9	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
RE1	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE10	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
RE12	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
RE13	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE14	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE22	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
RE29	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE39	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RE40	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
RE41	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
RIC1	AH13-00009A	IC ASIC;KS1462B,DVD-M201/XAA,80,+5V,-4	
RL11	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
RL3	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
RQ1	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT-	
RQ2	0501-000279	TR-SMALL SIGNAL;KSA1182-Y,PNP,150mW,SOT-	
RR1	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
RR10	2007-000312	R-CHIP;10ohm,5%,1/4W,TP,3216	
RR12	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
RR13	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
RR14	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
RR15	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
RR16	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
RR2	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
RR21	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
RR22	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
RR23	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
RR24	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608	
RR26	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
RR3	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
RR32	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
RR33	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
RR34	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
RR36	2007-001235	R-CHIP;910Kohm,5%,1/10W,TP,1608	
RR37	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
RR4	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608	
RR6	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
RR7	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608	
RR8	2007-000312	R-CHIP;10ohm,5%,1/4W,TP,3216	
RR9	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
SC10	2203-001634	C-CER,CHIP;33nF,10%,50V,X7R,TP,1608,1.6m	
SC11	2203-000715	C-CER,CHIP;3.3nF,10%,50V,X7R,TP,1608,-	
SC12	2203-000140	C-CER,CHIP;1.5nF,10%,50V,X7R,TP,1608,-	
SC13	2203-001652	C-CER,CHIP;470nF,+80-20%,16V,Y5V,TP,1608	
SC14	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC16	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
SC17	2203-001126	C-CER,CHIP;0.68nF,10%,50V,X7R,TP,1608	
SC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	

Loc.No	Part No	Description ; Specification	Remark
SC19	2203-002398	C-CER,CHIP;22nF,10%,50V,X7R,TP,1608	
SC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC21	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC23	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
SC24	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-	
SC25	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
SC26	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-	
SC27	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC28	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC29	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC32	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC33	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
SC34	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608	
SC35	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC36	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC37	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC38	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC39	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
SC40	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
SC41	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
SC42	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC43	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
SC44	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC45	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC46	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC47	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC48	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
SC49	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC50	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC52	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC54	2203-001222	C-CER,CHIP;820pF,10%,50V,X7R,TP,1608,-	
SC55	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC56	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC57	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC58	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC59	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC60	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC61	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC62	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC63	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC7	2203-001222	C-CER,CHIP;820pF,10%,50V,X7R,TP,1608,-	
SC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
SC90	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-	
SE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
SE11	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
SE2	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
SE3	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
SE4	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5	
SE6	2401-001225	C-AL;4.7uF,20%,16V,GP,TP,3x5,5	
SE7	2401-001225	C-AL;4.7uF,20%,16V,GP,TP,3x5,5	
SE8	2401-001225	C-AL;4.7uF,20%,16V,GP,TP,3x5,5	
SE9	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
SIC1	AH13-00006A	IC ASIC;KS1454,DVD-611/XAA,160,+3.3V,+	
SIC2	1105-001243	IC-DRAM;416C256,256KX16BIT,SOJ,40P,400	
SIC3	1003-001521	IC-MOTOR DRIVER;FAN8727,QFPH,48P,550MIL,	
SIC4	0801-002097	IC-CMOS LOGIC;7ST08,AND GATE,SOP,5P,110M	
SJACK	3722-001375	JACK-DIN;4P,-,NI,BLK,-	
SPKJ	3716-001202	TERMINAL-BLOCK;ANGLE,12P,2.30MM,1KV,-	
SQ1	0504-000156	TR-DIGITAL;KSR2103,PNP,200MW,22K/22K,SOT	
SR1	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608	
SR14	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
SR15	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
SR16	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608	

Loc.No	Part No	Description ; Specification	Remark
SR18	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608	
SR19	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
SR2	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
SR20	2007-001235	R-CHIP;910Kohm,5%,1/10W,TP,1608	
SR21	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
SR23	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
SR24	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608	
SR25	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	
SR26	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
SR27	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
SR29	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
SR30	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
SR31	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
SR32	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608	
SR4	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
SR40	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
SR44	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608	
SR48	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
SR49	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR50	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR51	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR55	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR56	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR57	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
SR58	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
SR59	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608	
SR60	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608	
SR61	2007-000107	R-CHIP;470Kohm,5%,1/10W,TP,1608	
SR67	2007-000034	R-CHIP;1OHM,5%,1/4W,DA,TP,3216	
SR68	2007-000034	R-CHIP;1OHM,5%,1/4W,DA,TP,3216	
SR69	2007-000655	R-CHIP;27Kohm,5%,1/10W,TP,1608	
SR70	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
SR71	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
SR72	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
SR73	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
SR74	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
SR75	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	
SR76	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608	
SR77	2007-000092	R-CHIP;15Kohm,5%,1/10W,TP,1608	
SR79	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
SR8	2007-000799	R-CHIP;360ohm,5%,1/10W,TP,1608	
SR9	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608	
SY1	2801-000261	CRYSTAL-UNIT;33.8688MHZ,50PPM,28-AAA,12P	
VC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC11	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC12	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,TP,1608	
VC16	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC17	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
VC9	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
VE1	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
VE11	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
VE13	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
VE5	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5	
VE7	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
VE9	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
VIC1	1201-001836	IC-VIDEO AMP;MM1567AJBE,SOP,34P,300MIL,-	
VL5	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
VL7	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VL8	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
VR1	2104-001068	VR-SMD;10Kohm,25%,1/20W,TOP	
VR17	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR18	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR19	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR20	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR21	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
VR28	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
VR30	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
VR32	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
VR33	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
VZ1	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ2	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ3	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
VZ4	0403-001083	DIODE-ZENER;UDZ9.1B,9.1V,8.85-9.23V,200m	
ZC1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC2	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC20	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC21	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC22	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC23	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC24	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC25	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC26	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC27	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC28	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC29	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC3	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC30	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC31	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC32	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC33	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC34	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC35	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC36	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC37	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC38	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC39	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC4	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC40	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC41	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
ZC42	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC43	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC44	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC45	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608,-	
ZC46	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
ZC5	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC59	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
ZC6	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC60	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
ZC61	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608	
ZC62	2203-001567	C-CER,CHIP;0.01nF,0.5pF,50V,NP0,TP,1608	
ZC63	2203-000384	C-CER,CHIP;0.015NF,5%,50V,C0G,TP,1608	
ZC65	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC66	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC67	2203-000626	C-CER,CHIP;0.022NF,5%,50V,C0G,TP,1608	
ZC7	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC76	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC77	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZC8	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608	
ZE3	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
ZE4	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
ZE5	2401-001479	C-AL;470uF,20%,10V,GP,TP,-,-	
ZE6	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
ZE7	2401-003107	C-AL;47uF,20%,16V,GP,TP,5x7,5	
ZIC1	1204-002039	IC-DECODER;ZR36732,MQFP,160P,28X28MM,PLA	
ZIC2	1105-001305	IC-DRAM;4S641632,1MX16X4BIT,TSOP,54P,4	
ZIC4	0801-002097	IC-CMOS LOGIC;7ST08,AND GATE,SOP,5P,110M	
ZL1	2703-000398	INDUCTOR-SMD;10uH,10%,3225	
ZL111	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	

Loc.No	Part No	Description ; Specification	Remark
ZL13	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
ZL15	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
ZL2	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
ZL3	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
ZL4	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
ZL5	3301-001419	BEAD-SMD;-,220,-,500,TP,-,0.3	
ZL7	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
ZL8	3301-000353	BEAD-SMD;120ohm,2x1.25x0.9mm,200mA,TP,,	
ZR2	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR23	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR3	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR30	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR31	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608	
ZR32	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR33	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR34	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR35	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR36	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ZR37	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
ZR38	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
ZR39	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
ZR4	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR40	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608	
ZR41	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ZR43	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
ZR44	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608	
ZR46	2011-000816	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP	
ZR47	2011-000816	R-NET;100OHM,5%,1/16W,L,CHIP,8P,TP	
ZR49	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR5	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608	
ZR50	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR51	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR52	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR53	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ZR54	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ZR55	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608	
ZR56	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
ZR57	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
ZR60	2007-000593	R-CHIP;22ohm,5%,1/8W,TP,2012	
ZR61	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
ZR62	2007-000658	R-CHIP;27ohm,5%,1/8W,TP,2012	
ZR63	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012	
ZR64	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608	
ZR66	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
ZR67	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
ZR68	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
ZR69	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608	
ZR8	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608	
ZY1	2801-004065	CRYSTAL-UNIT;27MHZ,10PPM,28-AAM,20PF,20O	
603	**AC94-00224A**	**ASSY PCB-SMPS;CHT-200,THEATER**	
BD2	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
BD3	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
BDV3	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
BDV4	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
C05	2201-000963	C-CERAMIC,DISC;1NF,20%,400V,Y5U,TP,9.5X6	⚠
C11	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
C12	2401-001200	C-AL;33UF,20%,50V,WT,TP,6.3X11,2.5	
C13	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
C14	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
C15	2401-003072	C-AL;1uF,20%,50V,WT,TP,5x11,2.5	
C16	2401-001200	C-AL;33UF,20%,50V,WT,TP,6.3X11,2.5	
C32	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
C36	2307-000103	C-FILM,LEAD-PCF;100nF,5%,50V,TP,-,5mm	
C37	2301-000129	C-FILM,LEAD-PEF;100nF,5%,50V,TP,10X9X4.3	
C38	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	

Loc.No	Part No	Description ; Specification	Remark
C39	2301-000402	C-FILM,LEAD-PEF;1nF,5%,50V,TP,5x7x2.8mm,	
CD34	2401-003480	C-AL;1000UF,20%,10V,LZ,TP,10X16MM,5	
CD50A	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
CV30	2401-003137	C-AL;330UF,20%,50V,WT,TP,10X16MM,5	
CV31	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
CV33	2401-001992	C-AL;2200UF,20%,10V,WT,TP,10X20MM,5	
CV34	2401-001126	C-AL;330uF,20%,25V,WT,TP,10x12.5,5	
CV35	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
D05	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D10	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
D36	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D37	0403-000713	DIODE-ZENER;MTZJ20B,20V,18.63-17.7V,500m	
D38	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
D801	0402-001562	DIODE-BRIDGE;TS6P05G,600,6A,SIP-4,ST	
DD33	0404-001180	DIODE-SCHOTTKY;SE55,45V,5000MA,TO-220A,B	
DD77	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
DV30	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
DV31	0402-001194	DIODE-RECTIFIER;UG2D,200V,2A,DO-204AC,TP	
DV32	0404-001225	DIODE-SCHOTTKY;SRAF560,60V,5000mA,ITO-22	
DV34	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
IC01	1203-002805	IC-PWM CONTROLLER;ICE2BS01,PDIP,8P,9.52X	
IC02	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
IC03	AC14-12006D	IC;KA431Z,TO-92,TAPING	
L31	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
LD50A	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
LV32	AC27-12001N	COIL CHOKE;10UH-15%,RA,K-30,Q80,150KHZ,-	
PB1	3301-000297	BEAD-AXIAL;25ohm,3.6x1.2x5.7mm,,TP,,,	
PC1	2301-001325	C-FILM,LEAD-PPF;330nF,10%,275V,TP,26x8.5	⚠
PC103	2301-000383	C-FILM,LEAD-PEF;10nF,5%,50V,TP,6x7x3.2mm	
PC113	2301-000008	C-FILM,LEAD-PEF;2.2nF,5%,50V,TP,5.5X7X3,	
PC13	2301-000402	C-FILM,LEAD-PEF;1nF,5%,50V,TP,5x7x2.8mm,	
PC14	2201-000863	C-CERAMIC,DISC;0.68NF,10%,50V,Y5P,TP,5X3	
PC2	2301-001325	C-FILM,LEAD-PPF;330nF,10%,275V,TP,26x8.5	⚠
PC3	2201-000963	C-CERAMIC,DISC;1NF,20%,400V,Y5U,TP,9.5X6	⚠
PC34	2307-000103	C-FILM,LEAD-PCF;100nF,5%,50V,TP,-,5mm	
PC41	2201-000129	C-CERAMIC,DISC;0.1NF,10%,1KV,Y5P,TP,7X4M	
PC4A	2201-000987	C-CERAMIC,DISC;2.2NF,20%,400V,Y5U,BK,12.	
PC5	2201-000987	C-CERAMIC,DISC;2.2NF,20%,400V,Y5U,BK,12.	
PC50	2401-003850	C-AL;1000UF,20%,50V,WT,TP,12.5 X 25	
PC9	2305-001029	C-FILM,LEAD-PEF;10nF,10%,630V,TP,12x9x12	
PCE10	2401-003072	C-AL;1uF,20%,50V,WT,TP,5x11,2.5	
PCE17	2401-003243	C-AL;150uF,20%,400V,WT,BK,25x30,10	
PCE27	2401-001902	C-AL;100uF,20%,50V,GP,-,6.3x11,2.5	
PCE6	2401-003850	C-AL;1000UF,20%,50V,WT,TP,12.5 X 25	
PCN1	3711-000178	CONNECTOR-HEADER;1WALL,2P,1R,3.96mm,STRA	
PCN2	AC39-00082A	CBF HARNESS;-,24AWG,-,13P,85,-,-,-,MOLEX	
PCN3	3711-000595	CONNECTOR-HEADER;BOX,10P,1R,2mm,ANGLE,SN	
PCN4	3711-000827	CONNECTOR-HEADER;BOX,2P,1R,2mm,STRAIGHT,	
PD14	0402-001195	DIODE-RECTIFIER;F1T4,400V,1.0A,TS-1,TP	
PD16	0402-001569	DIODE-RECTIFIER;-,400,16A,ITO-220,-	
PD17	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
PD18	0402-001569	DIODE-RECTIFIER;-,400,16A,ITO-220,-	
PD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
PD7	0402-000012	DIODE-RECTIFIER;UF4007,1KV,1A,DO-41,TP	
PFD1	3601-000296	FUSE-CARTRIDGE;250V,5A,TIME-LAG,CERAMIC,	⚠
PIC1	1203-001951	IC-PWM CONTROLLER;3844,DIP,8P,300MIL,PLA	
PIC3	0604-001028	PHOTO-COUPLER;TR,50-600%,250mW,DIP-4,ST	⚠
PIC5	AC14-12006D	IC;KA431Z,TO-92,TAPING	
PL1	AC29-00006A	FILTER LINE-NOISE;SLV-300D,CFOR137350V-0	⚠
PL2	AC29-00007A	FILTER LINE NOISE;SV-DVD7400,SQ 2626,0.6	⚠
PL3	AC27-00007A	COIL CHOKE;-,-,22UH,-,-,0.02OHM MAX,-,BA	
PQ1	0505-001667	FET-SILICON;SPA07N60C3,N,600V,4.3A,0.6OH	
PR102	2001-000055	R-CARBON;4.7KOHM,5%,1/4W,AA,TP,2.4X6.4M	
PR104	2001-000065	R-CARBON;10KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
PR111	2001-000071	R-CARBON;22KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
PR112	2001-000764	R-CARBON;43KOHM,5%,1/4W,AA,TP,2.4X6.4MM	

Loc.No	Part No	Description ; Specification	Remark
PR121	2001-000113	R-CARBON;18KOHM,5%,1/4W,AA,TP,2.4X6.4MM	
PR13	2005-001019	R-WIRE WOUND,NON;0.2ohm,1%,1W,AA,TP,4x12	
PR14	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
PR15	2001-000044	R-CARBON;1.2KOHM,5%,1/4W,AA,TP,2.4X6.4M	
PR16	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM	
PR2	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
PR21	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
PR22	2003-000855	R-METAL OXIDE(S);47Kohm,5%,3W,AA,TP,6x16	
PR24	2003-002020	R-METAL OXIDE(S);56Kohm,5%,2W,AF,TP,3.9x	
PR241	2003-002020	R-METAL OXIDE(S);56Kohm,5%,2W,AF,TP,3.9x	
PR242	2003-002020	R-METAL OXIDE(S);56Kohm,5%,2W,AF,TP,3.9x	
PR3	2004-001136	R-METAL;6.8Kohm,1%,1/4W,AA,TP,2.4x6.4m	
PR31	2001-001153	R-CARBON(S);470HM,5%,1/2W,AA,TP,2.4X6.4M	
PR41	2001-000588	R-CARBON;3.3KOHM,5%,1/4W,AA,TP,2.4X6.4M	
PR5	2006-000171	R-CEMENT;4.7ohm,5%,7W,CB,BK,10x13x39mm	
PR8	2001-000626	R-CARBON;300OHM,5%,1/4W,AA,TP,2.4X6.4MM	
PTD1	AC26-00010A	TRANS SWITCHING;EER-4042,J2A,SV-DVD3500A	⚠
PTD2	AC26-00012M	TRANS SWITCHING;EER-3531,2JA,DVD-CM200,-	⚠
PTH01	1404-001084	THERMISTOR-NTC;5ohm,15%,-,18mW/C,TP	⚠
Q1	0502-000416	TR-POWER;2SD1273P,NPN,2W,TO-220F,BK,800	
Q10	0505-001729	FET-SILICON;SPA04N60C3,N,600V,4.5A,0.85O	
R11	2001-000546	R-CARBON;270KOHM,5%,1/4W,AA,TP,2.4X6.4M	
R12	2001-000546	R-CARBON;270KOHM,5%,1/4W,AA,TP,2.4X6.4M	
R13	2001-000546	R-CARBON;270KOHM,5%,1/4W,AA,TP,2.4X6.4M	
R14	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R15	2001-000598	R-CARBON;3.3OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R16	2005-001184	R-WIRE WOUND,NON;0.33OHM,5%,1W,AA,TP,4.3	
R17	2001-000325	R-CARBON;120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R18	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R19	2001-000527	R-CARBON;22OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R20	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R21	2006-000273	R-CEMENT;27KOHM,5%,2W,CA,BK,6.4X6.5X18M	
R22	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R31	2001-000062	R-CARBON;470OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R33	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R34	2004-000869	R-METAL;3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
R35	2004-000459	R-METAL;2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
R36	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
R37	2001-000036	R-CARBON;330OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R38	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM	
R39	2008-000179	R-FUSIBLE(S);10ohm,5%,1/2W,AA,TP,2.5x6.5	
RV24	2001-001099	R-CARBON(S);2.7KOHM,5%,1/2W,AA,TP,2.4X6.	
ZD10	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
701	**AC94-00222A**	**ASSY PCB-F/TIMER;CHT-200,THEATER**	
C701	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C702	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
C703	2401-002165	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C704	2202-000173	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,1	
C705	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C706	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
C707	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
C711	2401-000118	C-AL;1000uF,20%,10V,GP,TP,10x12.5,5	
CN701	3710-001145	CONNECTOR-SOCKET;20P,1R,1.5mm,STRAIGHT,S	
CN702	3711-001062	CONNECTOR-HEADER;BOX,6P,1R,2mm,STRAIGHT,	
D703	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D704	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D705	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D706	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D707	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
D708	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
DT701	AC07-00063A	LED DISPLAY;LTG-0149AM,CHT-420/XAA,7 SEG	
IC701	1003-001561	IC-LED DRIVER;PT6961,SOP,32P,300MIL,-,40	
L703	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	
L704	2701-000002	INDUCTOR-AXIAL;100uH,10%,4298	

Loc.No	Part No	Description ; Specification	Remark
LD701	0601-001715	LED;ROUND,BLUE,3MM,475NM,3X5MM	
Q701	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T	
R702	2001-000832	R-CARBON;510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R703	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R704	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R705	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R706	2001-000837	R-CARBON;51KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R707	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R708	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R709	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R710	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R711	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R712	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RM701	0609-001189	MODULE REMOCON;HORIZONTAL,16.4MM,TR	
SW701	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW702	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW703	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW704	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW705	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW706	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW707	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW708	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW709	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW711	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW712	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW713	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW714	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW715	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW716	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
SW717	3404-001188	SWITCH-TACT;12V,50MA,100GF,6X6X5,SPST	
ZD703	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
ZD704	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
702	**AK92-00192A**	**ASSY OPT PCB-VOLUME;DVD-CM350,VOLUME**	
CN00	AC39-00083A	CBF HARNESS;-,26AWG,-,6P,83,-,-,-,MOLEX	
VR101	3406-001082	SWITCH-ROTARY;DC 5V,1MA,24PULSE/NO CLICK	
-	**-**	**ASSY-HOUSING PCB;DVD-M101,MILLENO DECK(B**	**S.N.A**
HCN1	AH39-00266B	CONNECT WIRE;-,#26,-,-,-,WHT/BLK,-,-,-,-	
HSW1	3409-001119	SWITCH-DETECTOR;5V DC,1.0A,DPST,30gf,-	

MEMO